

CS5-LAN

FEATURES

- Accepts standard RS-422 CS5 signal and converts to UDP/NTP network protocol
- Generates a CS5 Ethernet-based (LAN) event code output from a CS5 asynchronous ASCII RS422 input
- WinDiscovery software utility included - provides easy configuration of CS5-LAN Injector to network
- Status lights indicates RS-422 input / LAN multicasting
- Requires the use of CAT5 spare pair (pins 7 & 8 of RJ-45) for CS5 input
- Reset button for quick default to factory settings
- Configuration is saved to non-volatile memory and survives power losses



Rack mountable with RM4



SPECIFICATIONS

Connectors

- > Ethernet - RJ45 CS5 Output
- > 2 mm threaded locking power jack
- > USB port for PC configuration

Operating Parameters

- > Temperature: 0 to 60°C
- > Humidity: Up to 90% (non-condensing at +25°C)

Compliance

- > FCC
- > CE Marked
- > ROHS
- > ANSI

Physical

- > Size: 6.44w x 4.06h x 1.44d in (16.4w x 10.32h x 3.65d cm)
- > Weight: 16 oz (454 g)

Power Supply

- > 12VDC external wall mount
- > Power consumption < 10W

MASTERCLOCK, INC.

5-YEAR LIMITED PARTS & LABOR WARRANTY

MADE IN THE USA

phone (USA and Canada):
1-800-940-2248

phone (international):
+1-636-724-3666

email:
sales@masterclock.com

online:
www.masterclock.com